

Everyone deserves great cellular signal





POWERFUL

Boost coverage for up to 3,000 sq. ft. Great for areas with very weak signal.

WIRELESS CONNECTIVITY

Wirelessly connect up to 50 cellular devices, including phones, smart phones, tablets and data cards.

NETWORK COMPATIBILITY

Boosts all 3G, 4G/LTE & 5G networks. Works on all technologies including CDMA, PCS, HSPA, HSPA+, AWS, and LTE.

AUTO SHUT OFF

Automatically shuts down the device in case of oscillation or an overloaded signal in order to prevent interference.

HOW A Uniden LI65XC BOOSTER KIT WORKS



ALL MAJOR CANADIAN CARRIERS
but not limited too

* Coverage varies on input signal







Uniden L65XC BOOSTER TECHNICAL SPECIFICATIONS

RF Parameter		Uplink	Downlink	
Frequency Range	LTE Lower A+B Block	698 ~ 716 MHz	734 ~ 746 MHz	
	LTE Upper C Block	776 ~ 787 MHz	746 ~ 757 MHz	
	CDMA	824 ~ 849 MHz	869 ~ 894 MHz	
	PCS	1850 ~ 1915 MHz	1930 ~ 1990 MHz	
	AWS	1710 ~ 1755 MHz	2110 ~ 2155 MHz	
Band Width	LTE Lower A+B Block/Uppe	er C Block 1	8 MHz / 11 MHz	
	CDMA/PCS/AWS	25 MH	25 MHz / 65 MHz / 45 MHz	
Max Gain	LTE Lower A+B Block		65 dB	
	LTE Upper C Block		65 dB	
	CDMA		65 dB	
	PCS		65 dB	
	AWS		65 dB	
Max. Output Power		17 dBm	17 dBm	
AGC (Step Attenuation)		31 dB / 1 dB step		
Inter-Modulation		≤ - 19 dBm	≤ - 19 dBm	
Spurious Emission		≤ - 30 dBm ~ ≤ - 36 dBm		
Electrical Parame	eter			
Power Supply		Input AC 90 ~ 240V, Output DC 12 V / 3 A		
Impedance		50 ohm		
Mechanical Para	meter			
I/O Port		N-Female		
Dimensions		200 * 117 * 40 mm		
Weight		≤1 Kg		
Environment Par	ameter			
Operating Temperature		-25 °C ~ +55 °C		
Relative Humidity		5% - 95%		
Environment Conditions		IP40		

